



## Specifications Osram Dulux D 18W 827 | Extra Warm White - 2-Pin

[View Product](#)

### General Information

|                             |                            |
|-----------------------------|----------------------------|
| SKU                         | 161930                     |
| EAN                         | 4050300011462              |
| Brand                       | Osram                      |
| Manufacturer Name           | DULUX D 18W/827 G24D-2 FS1 |
| Full box quantity           | 10                         |
| Any Lamp all-in warranty    | 1 Year                     |
| Energy efficiency class     | G                          |
| Energy efficiency class old | A                          |
| Average Lifetime (h)        | 10000                      |

### Technical Information

|                             |                       |
|-----------------------------|-----------------------|
| Technology                  | Fluorescent           |
| Dimmable                    | Not Dimmable          |
| Cap / Base                  | G24d-2 (2-pins)       |
| Number of pins              | 2                     |
| Colour Code                 | 827 Extra Warm White  |
| Colour temperature (Kelvin) | 2700 Extra Warm White |
| Colour Rendering (Ra)       | 80-89                 |
| Colour of Light             | White                 |
| Light colour options        | Single Color          |

|                          |                    |
|--------------------------|--------------------|
| Luminous Efficacy (lm/W) | 66.7               |
| Product Type Category    | PL-C / Dulux D D/E |

## Lamp Information

|                |           |
|----------------|-----------|
| Series         | Dulux     |
| Type of sensor | No Sensor |

## Dimensions

|               |     |
|---------------|-----|
| Length (mm)   | 153 |
| Height (mm)   | 153 |
| Diameter (mm) | 11  |

## Why Any-lamp?

 Order from the **largest lighting specialist** in Europe  **Customised** quotation

 Up to **7 years warranty**  **Easy** return process